



Base Lights & Light Trays

Base Lights and Gear Trays for Illuminated Traffic Bollards

The Haldo Base box is manufactured in die cast aluminium alloy LM6 and features Base flanges which include holes for fixing with rag bolts if required.

Both lead in tube and a gland fit options are available. Cable entry is through the rear of base box and is sealed by heat shrink sleeves, cold shrink sleeves, cable entry seal, or cold pour compounds. The lid is secured with four stainless steel bolts.

The Haldo base box achieves an IP67 rating, and all industry standard Traffic bollard Shells are compatible. Spares such as lenses and replacement lids, locks and Tri keys are available.

Features:

- Die Cast LM6 Base Box
- Cable Entry or Gland Fit Available
- Lid with 4 Bolts or Quick Release
- Fits All Industry Standard Illuminated Bollard Shells
- With Or Without photocell
- White 5000K LED
- Average Lifespan 100,000 Hours
- 230v or 24v versions available
- Gear trays options for all Industry Standard bases
- Replacement Components available
- IP67 Base Box
- Flood Resistant LED trays and Bases



AVAILABLE TO
BUY ONLINE



Haldo | 221 Bowling Back Lane | Bradford | West Yorkshire | BD4 8SJ
www.haldo.com | 01284 754043 | sales@haldo.com





Base Lights & Light Trays

Base Lights & Gear Trays

LED Light Trays:

The efficient LED light tray has a sealed domed lens which is housed in the existing **IP67** sealed basebox for excellent flood resistance. Light output conforms to **BS EN 12899** and the LED light Tray consumes 6 watts of power.

The light tray is designed to illuminate any industry standard 270mm to 600mm traffic bollards. UMSUG code is 42 0006 0000 100. Haldo's LED light trays are available as both 230v and 24v and versions are available to fit various manufacturers industry standard baselights.

Order Codes and Descriptions:

Code	Description
C2/BL2/16LED/T/2	240V LED Gear Tray for Haldo Baselight, No photocell
C2/BL2/16LED/T/2/S	240V LED Gear Tray for Haldo Baselight, with photocell
C2/BL2/16LED/24V/2	24V LED Gear Tray for Haldo Baselight, No photocell
C2/BL2/16LED/24V/2/S	24V LED Gear Tray for Haldo Baselight, with photocell
C2/BL2/19LED/T/2	Haldo Basebox with 240V LED Gear Tray, No photocell
C2/BL2/19LED/T/2/S	Haldo Base Box with 240V LED Gear Tray for Haldo, with photocell
C2/BL2/19LED/24V/2	Haldo Base Box with 24V LED Gear Tray, No photocell
C2/BL2/19LED/24V/2/S	Haldo Base box with 24V LED Gear Tray, with photocell
C2/BL2/18-LG	Replacement lid WITHOUT Lens
C2/BL2/18-3	Replacement lid With 3MM Lens
C2/BL2/18-5	Replacement lid With 5mm Lens
C2/BL2/17	Base box with board, Earth cable, 3 way block & pin (for Fluorescent installs) and 4 lid bolts
C2/BL2/17A	Base box with board, Earth cable, and 4 lid bolts (for LED installs)

- o Add Suffix GF for Gland Fit
- o Add Suffix S for a Photocell
- o Add Suffix QR for Quick Release Lid

e.g. 230v LED Base light with Gland Fit cable entry and Photocell is C2/BL2/19LED/T/2/S/GF



Haldo | 221 Bowling Back Lane | Bradford | West Yorkshire | BD4 8SJ
www.haldo.com | 01284 754043 | sales@haldo.com

